

Partner: Rane
Model: RPM88
Device Type: Mixer



GENERAL INFORMATION

SIMPLWINDOWS NAME:	Rane RPM88 Source Selector
CATEGORY:	Mixer
VERSION:	1.0
SUMMARY:	Selects a source on a Rane RPM88 source selector block.
GENERAL NOTES:	<p>This module will select a source on the Rane RPM88 source selector block.</p> <p>NOTE: As this device requires UDP/IP for control, it can only be controlled using a 2 series processor with an Ethernet port.</p>
CRESTRON HARDWARE REQUIRED:	C2ENET
SETUP OF CRESTRON HARDWARE:	UDP/IP Port 5000d
VENDOR FIRMWARE:	rpm88_fw2_3_21
VENDOR SETUP:	None
CABLE DIAGRAM:	None

CONTROL:

Input_*	D	Pulse to select the desired input.
Poll	D	Pulse to poll the RPM88 for the currently selected input.
From_Device\$	S	Serial signal to be routed from a UDP/IP Communication symbol.
Selector Type	P	Select the type of selector to be controlled. This is from a drop down list.
PID	P	Enter the PID number for the selector from the Rane DragNet software.

Partner: Rane
Model: RPM88
Device Type: Mixer

**FEEDBACK:**

Input_*_Fb	D	High to indicate the currently selected input.
Poll_Busy	D	High to indicate that the device is being polled for the current input.
To_Device\$	S	Serial signal to be routed to a UDP/IP Communication symbol.

TESTING:

OPS USED FOR TESTING:	PRO2: 3.117
COMPILER USED FOR TESTING:	2.05.20
SAMPLE PROGRAM:	Rane RPM88 Demo PRO2
REVISION HISTORY:	V. 1.0 – Original Release.